



TECHNIC 10000 E

PORTABLE POWER

Generating Sets Range TECHNIC

PRODUCT ADVANTAGES

- Entire group guaranteed 3 years
- KOHLER air-cooled industrial engine
- Electric starter with batteries without maintenance
- Large Autonomy
- Connection interface equipped with an hour meter and the APM202 control unit

The APM202 control panel displays overspeed, starting failure, oil pressure, battery and temperature

Range TECHNIC

A long run time equipment that can withstand extreme conditions, for daily professional use.



TECHNIC 10000 E

GENERAL SPECIFICATIONS

Range	TECHNIC
Frequency (Hz)	50 Hz
Max power (kW) *	10.30
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	33
75% cons. (l/h) *	5
75% Autonomy (h) *	6.60
Sound power level guaranteed LwA dB(A)	97
Acoustic pressure level @1m in dB(A)	83
Acoustic pressure level @7m in dB(A)	69

ENGINE SPECIFICATIONS

Engine brand	KOHLER
Engine type	CH680
Distribution	O.H.V.
Start	Electrical
Oil shutdown	Oui
Displacement (cm ³)	674
Oil system capacity including filters (L)	1.90

ALTERNATOR SPECIFICATIONS

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

PLUGS AND PANEL DESCRIPTIVE

1 230V 10/16A socket - circuit breaker + 1 230V 16A socket - circuit breaker + 1 230V 32A socket - circuit breaker + hour meter + indicator + APM202

DIMENSIONS AND WEIGHT

Length (cm)	89.50
Width (cm)	57
Height (cm)	77
Dry Weight (kg)	167

PACKAGING

Packaging type	Box / Pallet
Length (cm)	91
Width (cm)	58.50
Height (cm)	92
Weight (kg)	180
Pallet type	
Number of box by pallet	0
Pallet height (cm)	0
weight of the packaged Pallet (kg)	0

ACCESSORIES SUPPLIED



Funnel
Battery without maintenance



User and maintenance manual
Hour meter

OPTIONS



R02B	This set includes a differential switch, a hour meter, the plugs and a thermal circuit breaker.
-------------	---



RSTART2	Remote control in order to start or stop the generating set until a distance of 50 meters (needs the APM202 control panel)
----------------	--



VERS050	Switches over automatically if the mains fails, 40A or 100A 1P or if the mains fails, 25A or 40A 3P (needs the installation of a APM202 control panel). Includes the battery charger.
----------------	---



R05M	The manual changeover switch is used to connect and disconnect a generating set manually to a domestic circuit when there is a power cut.
-------------	---



RKB2	Trolley kit for the generating sets superior to 6kW
-------------	---



RKS5	Maintenance kit for KOHLER CH680 engine.
-------------	--



Adaptor for industrial sockets	ERR:not found in dict valeurs
---------------------------------------	-------------------------------



RH2	Cover for SDMO 's generating sets, welding sets and water pumps
------------	---



RPM	Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V
------------	---